## Audio/Video Selector

# **JBOX 5-3**






## **Key Features**

The JBOX 5-3 allows to connect together all the Audio/Video devices used in normal domestic applications.

The JBOX 5-3 is able to connect up to three independent vision, transponder and recording devices, selecting the Audio/video signal, for each one of them, from a set of five possible independent sources. The choice of the available source is done using one selection push button and one colored lighting indicator on each output.



#### User's Note

The JBOX 5-3 is able to connect up to three TV screens to a set of independent devices such as home cinema, stereo, videogames, lap-top, DVD reader, UHF transponder, SAT/DBV-T decoder.

It also allows to recorder two independent TV signals wile there is a different third one under vision on the connected TV screen.

Audio signals are in stereo mode on every selected connections.

## **Technical Characteristics**

## **ELECTRICAL**

Supply Voltage: 9 – 12 Vdc @ 100mA Consumption: 1 Watt maximum External AC/DC power supply

#### **MECHANICAL**

Dimension : 200 x 100 x 30 (h)

Weight : 300 grams
Material : ABS
Color : black

#### **CONNECTIONS**

Inputs : 4x Scart (RGB/S-VHS)

1x Cinch A/V

Outputs : 2x Scart (RGB/S-VHS)

1x Cinch A/V

#### CONTROL

Selection : 1 pushbutton on each output

Status : 3 LED on each input

# Mechanical Layout (Unit: mm)

